

# *Compaq StorageWorks*

## **SAN Switch 16 Release Notes**

These release notes contain late-breaking and supplemental information for the Compaq StorageWorks SAN Switch 16.

### **Firmware Version 2.03a**

The SAN Switch 16 comes with the latest version of the firmware installed. A copy of the latest version of the firmware, v2.0.3a as of this date, is also contained on the Compaq StorageWorks SAN Switch Software CD. Instructions for downloading the firmware and the required loaders are also contained on the CD. This firmware is for the Compaq StorageWorks SAN Switch only and will not work if loaded into older Compaq StorageWorks Fibre Channel Storage Switches.

## Compatibility

The Compaq StorageWorks SAN Switch software (version 2.0 and above) is compatible with the Compaq StorageWorks Fibre Channel Switch software (Version 1.6c or 1.6d), allowing both types of switches to operate in the same fabric. To accomplish this compatibility, the SAN Switch 16 must be configured to use a specific addressing mode. This mode is designated “VC Encoded Address Mode.”

Invoke this mode using the `configure` command, as described in Appendix A of the *Compaq StorageWorks SAN Switch Fabric Operating System Management Guide*. When using this compatibility mode, the maximum switch count in a fabric is reduced from 239 to 32, and the maximum number of multicast groups is reduced from 256 to 31.

If the compatibility mode is not set, the following error message displays when you interconnect a SAN Switch 16 and a Compaq StorageWorks Fibre Channel Switch:

FABRIC, SEGMENTED, LOG\_WARNING

Description: Fabric segmented.

Probable Cause: Incompatible fabric parameters/switches or conflict zones.

Action: Reconfigure fabric or zones. See `configure` command.

## CD Directory Structure

This section lists the contents of the Compaq StorageWorks SAN Switch Software CD, including the names and descriptions of the files that contain release notes for the SWCC client and agent for managing the SAN Switch 16.

- Dsggb
  - Docs
    - readme.txt (CPQ SWK RELEASE NOTES; late-breaking doc changes)
    - ek-bcp24-ia.pdf (CPQ SWK SAN Switch 8 Installation and Hardware Guide)
    - ek-bcp28-ia.pdf (CPQ SWK SAN Switch 16 Installation and Hardware Guide)
    - ek-p20ff-ga.pdf (CPQ SWK SAN Switch Fabric Operating System Management Guide)
    - ek-p20ps-ia.pdf (CPQ SWK SAN Switch Power Supply Installation Guide)
    - ek-p20ql-ga.pdf (CPQ SWK SAN Switch QuickLoop Management Guide)
    - ek-p20ww-ga.pdf (CPQ SWK SAN Switch Web Management Tools Reference Guide)
    - ek-p20zg-ga.pdf (CPQ SWK SAN Switch Zoning Reference Guide)
    - 161353-001.pdf (CPQ SWK SAN Switch 8 Configuration Poster)
    - 161354-001.pdf (CPQ SWK SAN Switch 16 Configuration Poster)
  - Firmware (Compaq StorageWorks Fibre Channel Firmware and updates)
    - firmwareupdate.txt (instructions for updating firmware)
    - v2.0.3a (switch firmware)
    - v2.0.1aFE.mib (Management Information Base for fabric)
    - v2.0.1aSW.mib (Management Information Base for switch)
    - v2.0.1aTRP.mib (Management Information Base for traps)
  - NTAlpha
    - Cat.exe (mover for upgrading firmware from an Alpha)
    - Rshd.exe (small server for upgrading firmware from an Alpha)
  - NTIntel
    - cat.exe (mover for downloading firmware from a PC)
    - rshd.exe (small server for upgrading firmware from PC)
- SWCC(SWCC software for managing the Compaq StorageWorks SAN Switch and the Compaq StorageWorks Fibre Channel Switch)
  - ccclient.txt (SWCC Client release notes)
  - fcswitch.txt (Switch Client release notes)
  - readme.txt (SWCC late breaking changes)
  - swccinstallguide.pdf (CPQ SWK Command Console for the SAN Switch Installation Guide)
- NTAlpha
  - Agent
    - Fibre (contains the installSHIELD kit)
  - Client (contains the installSHIELD kit for AppMgr)
    - Fibre (contains ISHIELD fibre applet kit)
- NTIntel
  - Agent
    - Fibre (contains the installSHIELD kit)
  - Client (contains the installSHIELD kit for AppMgr)
    - Fibre (contains ISHIELD fibre applet kit)
- Acrobat
  - Ar32e301.exe
  - other acrobat files

## **Known Issues**

This section describes the known issues and problems related to the SAN Switch 16 as of 9/4/99.

### **QuickLoop**

QuickLoop, with large numbers of looplets (16), can cause some adapters to time out during initialization, resulting in repetitive initializations.

### **Web Management Tools**

- Netscape 4.6 (IRIX) fails to load SwitchManager.html (coredump of Netscape or SwitchApplet cannot start error).
- When running the Web Management Tools firmware V2.0 on a switch, a fault does not show when you remove a power supply.

### **Switch Operating System**

- When connected to some Ethernet switches, the Compaq StorageWorks SAN Switch with 100BaseT sometimes fails to connect through Telnet and the GUI.
- Usernames can be changed from the admin page of the Web Management Tools. Usernames should be unique; however, if a username is changed to one that is already in use, no message displays stating that the username is not unique, and the original username changes to the duplicate value.
- The Port LED tab in the Port Detail View page of the Web Management Tools will not receive a status update after a reload in Netscape 4.0.
- Negative numbers in statistics of port display do not match with positive numbers in Telnet portStatsShow display.
- Zoning information still transfers through an E-port between a SAN Switch 8 to a SAN Switch 16, even if the SAN Switch 8 does not have fabric operating system license.

### **Supported Configurations**

This release supports cascading of switches. See Compaq Solutions Kits for supported configurations.

## **Cables**

Optical cables for the SAN Switch 16 must be ordered separately. The cables that are 500 meters or less should be multi-mode Fibre Channel cables. The cables that are longer than 500 meters should be single-mode. Multi-mode optical cables are connected to shortwave GBIC modules in the SAN Switch 16. Single-mode optical cables are connected to longwave GBIC modules in the SAN Switch 16. Multi-mode cables should use 50/125 optical fibers, SC Duplex connectors with a PC finish. Use of 62.5/125 should be restricted to situations where 62.5/125 optical fiber was previously installed and the link lengths are to be kept shorter than 200 meters. Single-mode cables typically use 9/125 optical fibers for distances up to 10 km.

## **GBIC Modules**

Giga Bit Interface Converter (GBIC) modules for the SAN Switch 16 must be ordered separately. The Compaq part number for the optical GBIC module for multi-mode cable is 234456-003. Two single-mode GBIC modules and a short single-mode test cable can be ordered in a kit (part number 340412-B21).

## **NOTICE**

The information in this document is subject to change without notice. COMPAQ COMPUTER CORPORATION SHALL NOT BE LIABLE FOR TECHNICAL OR EDITORIAL ERRORS OR OMISSIONS CONTAINED HEREIN; NOR FOR THE INCIDENTAL OR CONSEQUENTIAL DAMAGES RESULTING FROM THE FURNISHING, PERFORMANCE, OR USE OF THIS MATERIAL.

This document contains information protected by copyright. No part of this document may be photocopied or reproduced in any form without prior written consent from Compaq Computer Corporation. Product names mentioned herein are trademarks and/or registered trademarks of their respective companies.

© 1999 Compaq Computer Corporation. All rights reserved.  
Printed in the U.S.A.

First Edition (October 1999)  
Part Number EK-P28FR-AA. A01 / 161365-001